

PREPARING A TCU800 UPDATE USB

REQUIRES A COMPUTER AND A BLANK USB FLASH DRIVE AT LEAST 1GB IN SIZE
(THIS PROCEDURE ASSUMES YOU ARE USING WINDOWS 10)

WARNING: FOLLOWING THIS PROCEDURE WILL ERASE ALL FILES PREVIOUSLY STORED ON YOUR USB FLASH DRIVE

- 1 Are you using a flash drive that already has a TCU800 update package on it?

Yes


Skip to step 6.

No

Continue to step 2.


- 2 Insert a blank USB flash drive (at least 1GB) into your computer.

If the flash drive has existing files on it, they will be erased in the next step.




- 3

Hit the windows key  on your keyboard (or click the start button on your desktop) and type **"This PC."** Then hit the **Enter** key to open up your list of attached devices.



4 Find your usb device and right click it.

Select “**Format...**” from the context menu.




5 A window will pop up.

Make sure the entry under “File System” is set to **FAT32**.

Click **Start** at the bottom.

When the process completes, you’ll be ready to continue extracting the update onto the flash drive.



- 6 Download the TCU800 Update firmware at the DFS website.

<https://www.dataflowsys.com/dfs-customer-only-downloads/>

TCU800 Software Release / USB Update

VERSION DATE: 05/12/21


FIRMWARE VERSION: v5.7.2





- 7 Navigate to the downloaded file. It will should be named something like: *tcu800v5_latest.zip*.

Right-click the file and click "Extract All..."

Hint: Downloaded files are usually located in your "Downloads" folder in your home directory.




- 8 Click “**Browse...**” and navigate to the USB flash drive that was formatted in step 4.




- 9 If the following window appears, select **“Replace files in the destination.”**

Otherwise, continue.



- 10 Verify that the following folders/files appear in the **base directory** of USB drive. The version file may be different based on the current firmware release.



- 11 Safely remove the update USB by right-clicking it and select **“Eject.”**

The update USB can now be used to upgrade the firmware in a TCU800 by following procedure TCUOP0300: UPDATING A TCU800 OVER USB

